

UA590I

定向天线

Directional Antenna UA590I

UA SERIES



产品特性 Features

- ▶ 专业用于UHF频段发射及接收两用的定向天线，频宽涵盖470-1000MHz范围。
- ▶ 附带天线信号放大器，可以弥补长距离的电缆对信号造成的损耗。
- ▶ 有效增加信号接收距离及传输的稳定性。
- ▶ 采用低噪声及低互调失真设计。
- ▶ 天线具有良好的增益和方向性，强波器增益可调（-4~+11dB）。
- ▶ 天线信号输出端口BNC。
- ▶ Specialize in UHF band transmit and receive dual directional antenna, the frequency will be 470-1000MHz.
- ▶ The antenna signal can compensate the loss caused by the long distance cable.
- ▶ Increasing signal receiving distance and transmission stability .
- ▶ 1U standard metal cabinet.
- ▶ Improved gain and directivity, gain adjustable（-4~+11dB）.
- ▶ Signal output BNC connector.

参数规格 Specifications

频率范围	470-1000MHz	Frequency range	470-1000MHz
天线增益	7.5dBi	Antenna gain	7.5dBi
驻波比	<2:1	Standing-wave ratio(SWR)	<2:1
3 dB波速宽	垂直面90°，水平面120°	3 Db wave velocity width	Vertical 90°，horizontal 120°
系统抗阻	50欧姆	System impedance	50 ohm
接头	BNC	Connector	BNC
尺寸	270×270mm	Dimension	270×270mm
重量	250g	Weight	250g



广州市锐丰智能科技有限公司 A:广东省广州市番禺区市莲路石楼路段10号
T:020-3928 0043 F:020-39280123-8014 E:info@rfintell.com Z:511447 www.rfintell.com

Guangzhou Ruifeng Intelligence Technology Co., Ltd Address: No.10,Shilou Section,Shilian Road,Panyu District,Guangzhou,Guangdong,China
T:+86 2039280083 Mobile: +86 13609092324 F:+86-20-39280123-8014 E: mail:sales@rfintell.com Z:511447 www.rfintell.com